## ASUS PRIME A620M-E-CSM AMD A620 Socket AM5 micro ATX

Brand: ASUS Product code: 90MB1F50-M0EAYC

Product name: PRIME A620M-E-CSM

- AMD AM5 Socket: Ready for AMD Ryzen™ 7000 Series Desktop Processors
- Ultrafast Connectivity: PCle 4.0, 64Gbps M.2 slot, Realtek 1Gb Ethernet, USB 3.2 Gen 1 Type-A
- Comprehensive Cooling: PCH heatsink, hybrid fan headers and Fan Xpert 2+
- Aura Sync RGB Lighting: Onboard Addressable Gen 2 headers and Aura RGB header for RGB LED strips, easily synced with Aura Sync-capable hardware
- Two-way Al Noise Cancelation: Reduces background noise from the microphone and audio output for crystal-clear communication in games or video conferences
- ASUS Control Center Express: Real-time IT monitoring and management software for enhanced data protection

Prime A620M-E-CSM Mainboard Socket AMD A620 (Ryzen 7000, micro-ATX, DDR5 memory, PCle 4.0, BIOS Flashback, USB 3.2 Gen 2, Aura Sync)





Processor		Rear panel I/O ports	
Processor manufacturer * Processor socket * Compatible processor series * Supported processor sockets	AMD Socket AM5 AMD Ryzen 7000 Series Socket AM5	USB 2.0 ports quantity * USB 3.2 Gen 1 (3.1 Gen 1) Type-A ports quantity * Ethernet LAN (RJ-45) ports *	4 4 1
Memory Supported memory types * DDR Number of memory slots * 2 Memory slots type DIMI Memory channels Dual ECC compatibility Non- Supported memory clock speeds Supported memory clock speeds	-channel -ECC 0,5000,5200,5400,5600,5800,6000,6200,6400	PS/2 ports quantity VGA (D-Sub) ports quantity * HDMI ports quantity * HDMI version DisplayPorts quantity DisplayPort version Headphone outputs Line-in Microphone in	1 1 2.1 1 1.4 1
Unbuffered memory   V	ib	Network	
Storage controllers Supported storage drive types Supported storage drive interfaces*	HDD & SSD	Ethernet LAN Ethernet interface type Wi-Fi *	✓ Gigabit Ethernet ×
Number of HDDs supported Number of storage drives supporte RAID support RAID levels	4	Features  Motherboard chipset * Audio output channels * Component for *	AMD A620 7.1 channels PC
<b>Graphics</b> Parallel processing technology support *	Not supported	Motherboard form factor *  Motherboard chipset family *  Cooling type	micro ATX AMD Passive
Internal I/O USB 2.0 connectors * USB 3.2 Gen 1 (3.1 Gen 1) connectors *	2	Power source type Windows operating systems supported	ATX Windows 10, Windows 11

Internal I/O		Expansion slots	
Number of SATA III connectors * S/PDIF out connector	4	PCI Express x1 (Gen 3.x) slots PCI Express x16 (Gen 4.x) slots	2 1
Front panel audio connector	✓	Number of M.2 (M) slots	1
ATX Power connector (24-pin)	✓	BIOS	
CPU fan connector	✓	BIOS type *	UEFI AMI
Number of chassis fan connectors	2	BIOS memory size	256 Mbit
EPS power connector (8-pin)	✓	Packaging data	
Number of COM connectors	1	Package width	260 mm
TPM connector	<b>/</b>	Package depth	270 mm
12V power connector	✓	Package height	51.5 mm
RGB LED pin header	✓	Package weight	940 g
		Weight & dimensions	
		Width	226 mm
		Depth	221 mm
		Packaging content	
		Cables included	SATA
		User guide	✓



4711387236772

Disclaimer. The information published here (the "Information") is based on sources that can be considered reliable, typically the manufacturer, but this Information is provided "AS IS" and without guarantee of correctness or completeness. The Information is only indicative and can be changed at any time without notification. No rights can be based on the Information. Suppliers or aggregators of this Information do not accept any liability with regard to the content of (web)pages and other documents, including its Information. The publisher of the Information can not be held liable for the content of 3rd party websites that are linking this Information or are linked to from this Information. You as the User of the Information are solely responsible for the choice and usage of this Information. You are not entitled to transfer, copy or otherwise multiply or distribute the Information. You are obliged to follow the directions of the copyright owner(s) with regard to the use of the Information. Exclusively Dutch law is applicable. With regard to price and stock data on the site, the publisher followed a number of starting points, which are not necessarily relevant for your private or business circumstances. Therefore, the price and stock data are only indicative and are subject to changes. You are personally responsible for the way you use and apply this information. As a user of the Information or sites or documents in which this Information is included, you will adhere to standard fair use including avoidance of spamming, ripping, intellectual-property violations, privacy violations, and any other illegal activity.