ASUS PROART B760-CREATOR Intel B760 LGA 1700 ATX

Tuotemerkki : ASUS Tuotekoodi: 90MB1F20-M1EAY0

Tuotteen nimi: PROART B760-CREATOR

ASUS PROART B760-CREATOR. Suoritinvalmistaja: Intel, Prosessorin kanta: LGA 1700, Yhteensopivat prosessorit: Intel® Celeron®, Intel® Pentium® Gold, Intel® Core™ i3, Intel® Core™ i5, Intel® Core™ Tuetut muistityypit: DDR5-SDRAM, Sisäinen enimmäismuisti: 192 GB, Muistipaikkojen tyyppi: DIMM. Tuetut tallennusasemaliitännät: M.2, SATA III, Tuetut tallennusasematyypit: HDD & SSD, RAID-tasot: 0, 1, 5, 10. Ethernet-liitännän tyyppi: 2.5 Gigabit Ethernet. Komponentti (tuotteelle): PC, Emolevyn muototekijä: ATX, Emolevyn piirisarjan perhe: Intel





Processor		Rear panel I/O ports	
Processor manufacturer * Processor socket *	Intel LGA 1700	USB 3.2 Gen 1 (3.1 Gen 1) Type-A ports quantity *	4
	Intel® Celeron®, Intel® Pentium® Gold, Intel® Core™ i3, Intel®	USB 3.2 Gen 2 (3.1 Gen 2) Type-C ports quantity *	1
Compatible processor series *	Core™ i5, Intel® Core™ i7, Intel®	Ethernet LAN (RJ-45) ports *	1
	Core™ i9	HDMI ports quantity *	1
Supported processor sockets	LGA 1700	DisplayPorts quantity	1
Memory		Headphone outputs	1
Supported memory types *	DDR5-SDRAM	Line-in	✓
Number of memory slots *	4	Microphone in	✓
Memory slots type	DIMM	S/PDIF out port	✓
Memory channels	Dual-channel	Network	
ECC compatibility	Non-ECC		
Maximum internal memory *	192 GB	Ethernet LAN	~
Unbuffered memory	✓	Ethernet interface type	2.5 Gigabit Ethernet
Storage controllers		Wi-Fi *	X
Supported storage drive types	HDD & SSD	Features	
Supported storage drive interfaces *	M.2, SATA III	Motherboard chipset *	Intel B760
RAID support	✓	Audio output channels *	7.1 channels
RAID levels	0, 1, 5, 10	Component for *	PC
Graphics		Motherboard form factor *	ATX
•		Motherboard chipset family *	Intel
Parallel processing technology support *	Not supported	Windows operating systems supported	Windows 10 x64, Windows 11 x64
Internal I/O		Expansion slots	
USB 2.0 connectors *	2	PCI Express x1 (Gen 3.x) slots	1
USB 3.2 Gen 1 (3.1 Gen 1)	1	PCI Express x16 (Gen 4.x) slots	1
connectors *	·-	Number of M.2 (M) slots	3
Number of SATA III connectors *	4		

Internal I/O		BIOS	
Front panel audio connector	✓	BIOS memory size	128 Mbit
Front panel connector	✓	Clear CMOS button	✓
ATX Power connector (24-pin)	✓	Packaging data	
CPU fan connector	✓	Package width	338 mm
Number of chassis fan connectors	4	Package depth	273 mm
EPS power connector (8-pin)	✓	Package height	68 mm
Number of COM connectors	1	Package weight	2.43 kg
TPM connector	✓	Weight & dimensions	
Thunderbolt headers	1	Width	305 mm
12V power connector	✓	Depth	244 mm
RGB LED pin header	✓	Height	50 mm
Rear panel I/O ports		Packaging content	
USB 2.0 ports quantity *	4	Cables included	SATA
		Other features	
		Number of M.2 (E) slots	1





197105179721

0197105179721

Disclaimer. The information published here (the "Information") is based on sources that can be considered reliable, typically the manufacturer, but this Information is provided "AS IS" and without guarantee of correctness or completeness. The Information is only indicative and can be changed at any time without notification. No rights can be based on the Information. Suppliers or aggregators of this Information do not accept any liability with regard to the content of (web)pages and other documents, including its Information. The publisher of the Information can not be held liable for the content of 3rd party websites that are linking this Information or are linked to from this Information. You as the User of the Information are solely responsible for the choice and usage of this Information. You are not entitled to transfer, copy or otherwise multiply or distribute the Information. You are obliged to follow the directions of the copyright owner(s) with regard to the use of the Information. Exclusively Dutch law is applicable. With regard to price and stock data on the site, the publisher followed a number of starting points, which are not necessarily relevant for your private or business circumstances. Therefore, the price and stock data are only indicative and are subject to changes. You are personally responsible for the way you use and apply this information. As a user of the Information or sites or documents in which this Information is included, you will adhere to standard fair use including avoidance of spamming, ripping, intellectual-property violations, privacy violations, and any other illegal activity.